

VS1053 to VS1063 Migration Guide

Description

This document describes how to migrate from VS1053 to VS1063. It lists hardware and software differences and other considerations.

This document applies to all versions of VS1053 and VS1063.

Revision History			
Rev	Date	Author	Description
1.00	2011-05-04	HH	Initial revision.

Contents

Description	1
Table of Contents	2
1 General	3
2 Hardware	4
3 Application Considerations	4
3.1 Hardware Design	4
3.2 Software Considerations	4
4 SCI Registers	5
4.1 Changed: SCI_MODE	5
4.2 Changed: SCI_STATUS	5
4.3 Changed: SCI_WRAMADDR	5
5 User Applications	6
6 Audio Encoding	6
7 Extra Parameters parametric_x	6
8 Licenses	6
9 Latest Document Version Changes	7
10 Contact Information	8

1 General

VS1063 is pin-compatible with the VS1053 which makes migration from VS1053 to VS1063 very simple from a hardware point of view.

Major updates in VS1063 are:

- Added MP3, Ogg Vorbis, μ -law, A-law and G.722 encoding.
- Added codec mode.
- Removed MIDI and MPEG layer I (MP1) decoders.
- MPEG layers II and III: new, more robust and accurate decoding. MP3 is now full accuracy compliant. Highest MP3 bitrates and samplerates require $2.5\times$ clock.
- CRC checking added for layer III files that contain CRC. CRC checking can be disabled.
- Keeps track of the valid data in bit reservoir, which allows noiseless start of decoding in the middle of an mp3 file.
- Samplerate finetuning in parametric_x.rateTune.
- WRAMADDR 0xc0c0..0xc0ff is mapped to parametric_x structure.
- Support reading u_int32's (almost) atomically through WRAM.
- Reading of stream and audio buffer fill states possible.
- Proportional and fixed-width font in data ROM for standalone applications.
- WAV decoding supports 24-bit and 32-bit and floating-point formats.
- RIFF-WAV header is generated automatically in WAV encoding (and codec) modes. The user still needs to fix the RIFF size and data size fields to make them valid WAV files.
- Sample-exact samplerate and volume change.
- Added mono mode and pause mode for player (parametric_x.playMode)
- Added FLAC decoding upto 2 channels.
- Added VU meter.
- Added AD mixer.
- Added PCM mixer.
- Added Speed shifter.
- Added I2C memory boot option.
- AAC, WMA, MP3 and FLAC decoding can be individually disabled using bits in parametric_x.config1.

Some of these new features have required for the register interface to be changed accordingly.

2 Hardware

VS1053 and VS1063 share the same hardware, so there is no need to update PCB's for VS1063.

3 Application Considerations

This chapter gives general info on applications using VS1063.

3.1 Hardware Design

From a hardware point of view, VS1063 is a drop-in replacement for the VS1053.

Nevertheless, VS1063 has an option to boot from external I2C memory. If this functionality is required, GPIO0, GPIO4 and GPIO6 need to be connected accordingly. Read the VS1063 Datasheet chapter "I2C boot" for details.

3.2 Software Considerations

Basic operation of VS1053 and VS1063 similar: playing back audio files doesn't usually require any changes to the controller software, except for removing loading of the VS1053b Patches w/ FLAC Decoder package, or replacing it with a similar VS1063 Patches package when that becomes available.

Major changes to microcontroller software is only needed when the features new to the VS1063 are required, or if audio encoding is used.

Note: The VS1053 Patches w/ FLAC Decoder package, as well as any other VS1053 Patches or VS1053 Applications will not run on VS1063 without porting them first.

4 SCI Registers

VS1053 and VS1063 have a few differences in registers. The following chapters list these differences. See more info from VS1053 and VS1063 datasheets.

4.1 Changed: SCI_MODE

SM_EARSPEAKER_LO and SM_EARSPEAKER_HI register bits are removed from VS1063. A much more fine-grained 16-bit EarSpeaker tuning register is offered in the earSpeakerLevel field of the Extra Parameters structure. To port from old register values, see the following table:

VS1053		VS1063
SM_EARSPEAKER_HI	RF_EARSPEAKER_LO	earSpeakerLevel
0	0	0
0	1	12000
1	0	38000
1	1	50000

SM_STREAM has been removed from VS1063. The option was limited in VS1053 so it was decided it could be dropped from VS1063. To stream using VS1063, use samplerate finetuning

SM_ADPCM has been renamed SM_ENCODE because VS1063 can encode also in many other formats than only IMA ADPCM.

4.2 Changed: SCI_STATUS

SS_VER is 4 for VS1053, and 6 for VS1063.

SS_REFERENCE_SEL was inconvenient to use on VS1053 due to a firmware bug. With VS1063 the higher reference voltage 1.65 V can be used as described in the VS1063 datasheet ($AVDD \geq 3.3$ V).

4.3 Changed: SCI_WRAMADDR

More memory areas can now be accessed with this register.

5 User Applications

Because memory addresses have changed the user applications, plugins and patches are different between VS1053 and VS1063. Many of them are not needed anyway because VS1063 directly supports the functionality of many of VLSI's plugins and applications.

6 Audio Encoding

Audio encoding has changed considerably between VS1053 and VS1063. While the basic interface, namely reading data through SCI_HDAT0 and SCI_HDAT1 registers, is the same as before, both initializing and finalizing recording has changed significantly. Read chapter "Audio Encoding" of the VS1063 datasheet for details.

7 Extra Parameters `parametric_x`

The Extra Parameters `parametric_x` data structure has many new fields and effects, ranging from a fine-tuned playback speed shifter to a 5-channel equalizer. Read chapter "Extra Parameters" of the VS1063 Datasheet for details.

8 Licenses

Earlier MP3 decoder ICs from VLSI Solution, including the VS1053, have included the MP3 decoder license. The price for VS1063 also includes the MP3 encoding license from Fraunhofer IIS and Thomson.

9 Latest Document Version Changes

This chapter describes the most important changes to this document.

Version 1.01, 2011-05-24

- Corrected incorrect PDF title.

Version 1.00, 2011-05-04

- Initial revision.

10 Contact Information

VLSI Solution Oy
Entrance G, 2nd floor
Hermiankatu 8
FI-33720 Tampere
FINLAND

Fax: +358-3-3140-8288
Phone: +358-3-3140-8200
Email: sales@vlsi.fi
URL: <http://www.vlsi.fi/>